

1. $S \rightarrow a_2$
2. $S \rightarrow w_3 S_4$
3. $S \rightarrow i_5 S_6$
4. $S \rightarrow i_5 S_6 \epsilon S_8$
5. $S \rightarrow b_9 L_{10} n_{11}$
6. $L \rightarrow L_{10} S_{12}$
7. $L \rightarrow \epsilon$

	a	w	i	e	b	n	eof	S	L
0	s2	s3	s5		s9			1	
1							halt		
2	r1	r1	r1	r1	r1	r1	r1		
3	s2	s3	s5		s9			4	
4	r2	r2	r2	r2	r2	r2	r2		
5	s2	s3	s5		s9			6	
6	r3	r3	r3	s7	r3	r3	r3		
7	s2	s3	s5		s9			8	
8	r4	r4	r4	r4	r4	r4	r4		
9	r7	r7	r7		r7	r7			10
10	s2	s3	s5		s9	s11		12	
11	r5	r5	r5	r5	r5	r5	r5		
12	r6	r6	r6		r6	r6			

ACTION

GOTO